



Emergency power kit modul SAMCOM

## Description

**Samcom EMK-140-LED Emergency Module T8 LED** untuk lampu T8 LED tube 10 watt sampai 22 watt, produk di desain sangat kompak dalam ukuran kecil sehingga mempunyai kemudahan dalam instalasi pada berbagai tipe fixture. Produk ini dilengkapi dengan Hi-temperature Nickel Cadmium battery pack dan super terang indikator pengisian LED.

Kemudian built-in custom sirkuit paten Hybrid IC untuk meningkatkan kehandalan dan efisiensi dalam pengoperasian.

Aplikasi pemasangan dan pemakaian cocok untuk:

- penerangan lampu tangga darurat,
- penerangan lampu darurat exit,
- penerangan lampu emergency rumah sakit,
- penerangan lampu emergency apartemen,
- penerangan lampu emergency mall atau supermarket,
- dan berbagai lampu darurat jenis T8 LED untuk kebutuhan lainnya.

Fitur dan spesifikasi teknis **Emergency power kit modul SAMCOM** ini:

- Input voltage: 115Vac~230Vac 50/60Hz +-10%
- Battery: 6v 2,5AH High temp rated Nickel Cadmium
- Lamp used: 10 watt ~ 22 watt T8 LED Tube (110 ~ 230v)
- Rated period: 1h
- Mode: maintained / non-maintained
- Power consumption: <5VA
- Charge monitor: Super bright green LED 5mm
- Recharge period: 16~24h
- Emergency luminance: design range from 20~50%
- Charger: Hybrid controller charger
- Protection: low volt cut-off prevent over discharge
- Construction: Aluminium case
- Testing facility: Push button
- Dimension: (L)330mm\*(W)90mm\*(H)50mm
- Compliance CP 19:2000, SS263: par 2, IEC 598-2-22, AS 2293